

**Rekommenderad kabelarea vid 100 cm för CMP Inverter**

<b>W</b>	<b>V</b>	<b>Benämning</b>	<b>Artnr.</b>	<b>Kabelarea</b>	<b>Strömförbrukn. från batteri (Ah)</b>
<b>Modifierad Sinus</b>					
300	12	WHS-300-12V	PC 10421004	3,0 mm <sup>2</sup>	29
300	24	WHS-300-24V	PC 10421005	2,0 mm <sup>2</sup>	14
600	12	WHS-600-12V	PC 10421006	8,0 mm <sup>2</sup>	58
600	24	WHS-600-24V	PC 10421007	5,3 mm <sup>2</sup>	29
1000	12	WHS-1000-12V	PC 10421008	13,0 mm <sup>2</sup>	96
1000	24	WHS-1000-24V	PC 10421009	8,0 mm <sup>2</sup>	48
1700	12	WHS-1700-12V	PC 10421012	33,0 mm <sup>2</sup>	163
1700	24	WHS-1700-24V	PC 10421013	21,0 mm <sup>2</sup>	81
<b>Ren Sinus</b>					
300	12	INT-300-12V	PC 10421016	5,3 mm <sup>2</sup>	29
300	24	INT-300-24V	PC 10421017	5,3 mm <sup>2</sup>	14
600	12	INT-600-12V	PC 10421018	13,0 mm <sup>2</sup>	58
600	24	INT-600-24V	PC 10421019	13,0 mm <sup>2</sup>	29
1000	12	INT-1000-12V	PC 10421020	21,0 mm <sup>2</sup>	96
1000	24	INT-1000-24V	PC 10421021	21,0 mm <sup>2</sup>	48
1500	12	INT-1500-12V	PC 10421022	21,0 mm <sup>2</sup>	144
1500	24	INT-1500-24V	PC 10421023	21,0 mm <sup>2</sup>	72